



## DRAFT INTERNATIONAL STANDARD ISO/DIS 10133

ISO/TC 188

Secretariat: SIS

Voting begins on:  
2007-06-07

Voting terminates on:  
2007-11-07

INTERNATIONAL ORGANIZATION FOR STANDARDIZATION • МЕЖДУНАРОДНАЯ ОРГАНИЗАЦИЯ ПО СТАНДАРТИЗАЦИИ • ORGANISATION INTERNATIONALE DE NORMALISATION

# Small craft — Electrical systems — Extra-low-voltage d.c. installations

*Petits navires — Systèmes électriques — Installations à très basse tension à courant continu*

[Revision of second edition (ISO 10133:2000)]

ICS 47.080

### ISO/CEN PARALLEL ENQUIRY

The CEN Secretary-General has advised the ISO Secretary-General that this ISO/DIS covers a subject of interest to European standardization. **In accordance with the ISO-lead mode of collaboration as defined in the Vienna Agreement, consultation on this ISO/DIS has the same effect for CEN members as would a CEN enquiry on a draft European Standard.** Should this draft be accepted, a final draft, established on the basis of comments received, will be submitted to a parallel two-month FDIS vote in ISO and formal vote in CEN.

**To expedite distribution, this document is circulated as received from the committee secretariat. ISO Central Secretariat work of editing and text composition will be undertaken at publication stage.**

**Pour accélérer la distribution, le présent document est distribué tel qu'il est parvenu du secrétariat du comité. Le travail de rédaction et de composition de texte sera effectué au Secrétariat central de l'ISO au stade de publication.**

THIS DOCUMENT IS A DRAFT CIRCULATED FOR COMMENT AND APPROVAL. IT IS THEREFORE SUBJECT TO CHANGE AND MAY NOT BE REFERRED TO AS AN INTERNATIONAL STANDARD UNTIL PUBLISHED AS SUCH.

IN ADDITION TO THEIR EVALUATION AS BEING ACCEPTABLE FOR INDUSTRIAL, TECHNOLOGICAL, COMMERCIAL AND USER PURPOSES, DRAFT INTERNATIONAL STANDARDS MAY ON OCCASION HAVE TO BE CONSIDERED IN THE LIGHT OF THEIR POTENTIAL TO BECOME STANDARDS TO WHICH REFERENCE MAY BE MADE IN NATIONAL REGULATIONS.

RECIPIENTS OF THIS DRAFT ARE INVITED TO SUBMIT, WITH THEIR COMMENTS, NOTIFICATION OF ANY RELEVANT PATENT RIGHTS OF WHICH THEY ARE AWARE AND TO PROVIDE SUPPORTING DOCUMENTATION.

**PDF disclaimer**

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.

**Copyright notice**

This ISO document is a Draft International Standard and is copyright-protected by ISO. Except as permitted under the applicable laws of the user's country, neither this ISO draft nor any extract from it may be reproduced, stored in a retrieval system or transmitted in any form or by any means, electronic, photocopying, recording or otherwise, without prior written permission being secured.

Requests for permission to reproduce should be addressed to either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office  
Case postale 56 • CH-1211 Geneva 20  
Tel. + 41 22 749 01 11  
Fax + 41 22 749 09 47  
E-mail [copyright@iso.org](mailto:copyright@iso.org)  
Web [www.iso.org](http://www.iso.org)

Reproduction may be subject to royalty payments or a licensing agreement.

Violators may be prosecuted.

## Contents

Page

Foreword .....	iv
<b>1 Scope .....</b>	<b>1</b>
<b>2 Normative references .....</b>	<b>1</b>
<b>3 Terms and definitions .....</b>	<b>1</b>
<b>4 General requirements .....</b>	<b>3</b>
<b>5 Batteries .....</b>	<b>3</b>
<b>6 Battery-disconnect switch .....</b>	<b>4</b>
<b>7 Conductors .....</b>	<b>4</b>
<b>8 Overcurrent protection .....</b>	<b>6</b>
<b>9 Panel boards (switchboards) .....</b>	<b>6</b>
<b>10 Wiring connections and terminals .....</b>	<b>7</b>
<b>11 Socket outlets .....</b>	<b>8</b>
<b>12 Ignition protection .....</b>	<b>8</b>
<b>Annex A (normative) Conductor requirements .....</b>	<b>9</b>
<b>Annex B (normative) Information and instructions and to be included with owner's manual (ISO 10240) .....</b>	<b>11</b>
<b>Annex C (informative) Recommended system tests .....</b>	<b>12</b>
<b>Annex D (informative) Related standards and brief description of their contents .....</b>	<b>13</b>
<b>Bibliography .....</b>	<b>15</b>

## Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of technical committees is to prepare International Standards. Draft International Standards adopted by the technical committees are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75 % of the member bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights.

ISO 10133 was prepared by Technical Committee ISO/TC 188, *Small craft*.

This third edition cancels and replaces the second edition (ISO 10133:2000), which has been technically revised.

# Small craft — Electrical systems — Extra-low-voltage d.c. installations

## 1 Scope

This International Standard establishes the requirements for the design, construction and installation of extra-low-voltage direct current (d.c.) electrical systems which operate at nominal potentials of 50 V d.c. or less on small craft of up to 24 m length of hull including their propulsion engines.

## 2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO 6722, *Road vehicles — 60 V and 600 V single-core cables — Dimensions, test methods and requirements*

ISO 8846, *Small craft — Electrical devices — Protection against ignition of surrounding flammable gases*

ISO 10239, *Small craft — Liquefied petroleum gas (LPG) systems*

IEC 60529:1989, *Degrees of protection provided by enclosures (IP Code)*

IEC 60947-7-1, *Low-voltage switchgear and control gear — Part 7: Ancillary equipment; Section one: Terminal blocks for copper conductors*

## 3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

### 3.1

#### **equipotential bonding conductor**

normally non current carrying conductor used to put various exposed conductive parts of direct current electrical devices and extraneous conductive parts at a substantially equal potential

### 3.2

#### **engine negative terminal**

terminal on the engine to which the negative battery cable is connected

### 3.3

#### **craft's ground**

#### **craft's earth**

ground (earth) which is established by a conducting connection (intended or accidental) with the common ground (potential of the earth's surface), including any conductive part of the wetted surface of the hull

- 3.4 ignition-protected equipment**  
equipment designed and constructed in accordance with ISO 8846
- 3.5 overcurrent protection device**  
device, such as a fuse or circuit breaker, designed to interrupt the circuit when the current flow exceeds a predetermined value for a predetermined time
- 3.6 panel board (switchboard)**  
supporting panel on which are fixed devices for the purpose of controlling and/or distributing power on a craft, such as circuit breakers, fuses, switches, instruments and indicators
- 3.7 sheath**  
uniform continuous tubular protective covering of metallic or non-metallic material, generally extruded, such as moulded rubber, moulded plastics, woven sleeving or flexible tubing, around one or more insulated conductors
- 3.8 trip-free circuit breaker**  
mechanical switching device capable of making, carrying and breaking currents under normal circuit conditions and also making, carrying for a specified time and breaking currents under specified abnormal circuit conditions such as those of short circuit, and which are designed so that the resetting means cannot be manually held in place to override the current interrupting mechanism
- 3.9 accessible**  
capable of being reached for inspection, removal or maintenance without removal of permanent structure of the craft
- 3.10 readily accessible**  
capable of being reached quickly and safely for effective use without the use of tools
- 3.11 conduit**  
part of a closed wiring system of circular or non-circular cross section for insulated conductors and/or cables in electrical installations allowing them to be drawn in and/or replaced
- 3.12 cable trunking**  
system of closed enclosures comprising a base with a removable cover intended for the complete surrounding of insulated conductors, cables, cords and for the accommodation of other electrical equipment
- 3.13 system voltage**  
nominal voltage supplied to the d.c. distribution panel board (switchboard) from the power source
- 3.14 exposed conductive part**  
conductive part of electrical equipment, which can be touched and which is not normally live, but which may become live under fault conditions
- 3.15 fuse**  
device that by fusing of one or more of its specifically designed and proportioned components, opens the circuit in which it is inserted by breaking the current when this exceeds a given value for a sufficient time

NOTE The fuse comprises all the parts that form the complete device.

**3.15****fully insulated two wire d.c. system**

system in which the d.c. negative is isolated from the ground (earth), i.e. not connected to the water through a metallic hull, the propulsion system or earthed through the a.c protective conductor

**3.16****two wire d.c. system with negative ground (earth)**

system in which the d.c. negative is connected to the ground earth through a metallic hull, the propulsion system or other means

**4 General requirements**

**4.1** The system type shall be either a fully insulated two wire d.c. system or a two wire d.c. system with negative ground. The hull shall not be used as a current carrying conductor. Engine-mounted wiring systems may use the engine block as the grounded conductor.

**4.2** An equipotential bonding conductor, if fitted, shall be connected to the craft's ground (earth) to minimize stray current corrosion.

**4.3** Switches and controls shall be marked to indicate their use, unless the purpose of the switch is obvious and whose mistaken operation will not cause a hazardous condition.

**4.4** Protective devices such as circuit breakers or fuses shall be provided at the source of power, e.g the panelboard (switchboard), to interrupt any overload current in the circuit conductors before heat may damage conductor insulation, connections or wiring system terminals.

NOTE The selection, arrangement and performance characteristics should be such that the following is achieved:

- a) Maximum continuity of service to healthy circuits under fault conditions through selective operation of the various protective devices;
- b) Protection of electrical equipment and circuits from damage due to overcurrents by coordination of the electrical characteristics of the circuit or apparatus and the tripping characteristics of the protective devices.

**4.5** All d.c. equipment shall function over a voltage range at the battery terminals as follows:

— for a 12 volt system: 9 to 15 volts

— for a 24 volt system: 18 to 30 volts

Exception: Where the circuit includes equipment requiring a higher minimum voltage, the specified minimum voltage shall be used in the calculation of the conductor size. See Annex A.2.

**4.6** The length and cross sectional area of conductors in each circuit shall be such that the calculated voltage drop shall not exceed 1 % of the nominal battery voltage at any appliance when every appliance in the circuit is switched on at full load.

**5 Batteries**

**5.1** Batteries shall be permanently installed in a dry, ventilated location above anticipated bilge water level.

**5.2** Batteries shall be installed in a manner to restrict their movement horizontally and vertically considering the intended use of the craft, including trailering if applicable. A battery, as installed, shall not move more than 10 mm in any direction when exposed to a force corresponding to twice the battery weight.

**5.3** Batteries as installed in the craft shall be capable of inclinations of up to 30° without leakage of electrolyte. Means shall be provided in monohull sailing craft for containment of any spilled electrolyte up to inclinations of 45°.

**5.4** Batteries shall be installed, designed or protected so that metallic objects cannot come in unintentional contact with any battery terminal.

**5.5** Batteries, as installed, shall be protected against mechanical damage at their location or within their enclosure.

**5.6** Batteries shall not be installed directly above or below a fuel tank or fuel filter.

**5.7** Any metallic component of the fuel system within 300 mm and above the battery top, as installed, shall be electrically insulated.

**5.8** Battery cable terminals shall not depend on spring tension for mechanical connection to the battery terminals.

## **6 Battery-disconnect switch**

**6.1** A battery-disconnect switch shall be installed in the positive conductor from the battery or group of batteries connected to supply system voltage in a readily accessible location as close as practical to the battery or group of batteries.

The following constitute exceptions:

- a) outboard-powered craft with engine starting and navigation lighting circuits only;
- b) electronic devices with protected memory and protective devices such as bilge pumps and alarms if individually protected by a circuit breaker or fuse as close as practical to the battery terminal;
- c) engine/fuel tank compartment ventilation exhaust blower if separately protected by a fuse or circuit breaker as close as practical to the battery terminal;
- d) charging devices which are intended to be used when the craft is unattended (e.g. solar panels, wind generators) if individually protected by a fuse or circuit breaker as close as practical to the battery terminal.

**6.2** The minimum continuous rating of the battery switch shall be at least equal to the maximum current for which the main circuit breaker is rated and also the intermittent load of the starter motor circuit, or the current rating of the feeder conductor, whichever is less. A separate battery disconnect switch may be installed for the engine cranking motor circuit.

**6.3** Remote controlled battery disconnect switches, if used, shall also permit safe manual operation.

## **7 Conductors**

**7.1** Electrical distribution shall use insulated stranded copper conductors. See Annex A, Table A.1. Conductor insulation shall be of fire-retardant material, e.g. not supporting combustion in the absence of flame.

**7.2** Conductors not sheathed shall be supported throughout their length in conduits, cable trunking, or trays, or by individual supports at maximum intervals of 300 mm.

**7.3** Sheathed conductors and battery conductors to the battery disconnect switch shall be supported at maximum intervals of 300 mm with the first support not more than 1 m from the terminal, other sheathed conductors at maximum intervals of 450 mm.

**Exception:** Sheathed outboard starter motor conductors.

**7.4** Conductors which may be exposed to physical damage shall be protected by sheaths, conduits or other equivalent means. Conductors passing through bulkheads or structural members shall be protected against insulation damage by chafing.

**7.5** Conductors shall be sized as a minimum in accordance with Table A.1, or the conductor manufacturers rated current carrying capacity, based on the load to be supplied and allowable voltage drop for the load to be carried. Conductors in voltage critical circuits, such as starter motor circuits, navigation light and ventilation blower circuits, whose output may vary with system voltage, shall be sized in compliance with the component manufacturer's requirements. See 4.5 and 4.6.

**7.6** Each conductor longer than 200 mm installed separately shall have at least 1 mm<sup>2</sup> area. Each conductor in a multi-conductor sheath shall have at least 0,75 mm<sup>2</sup> area and may extend out of the sheath a distance not exceeding 800 mm.

An exception may be made for conductors of minimum 0,75 mm<sup>2</sup> which may be used as internal wiring in panel boards.

**7.7** A d.c. circuit shall not be contained in the same wiring system as an a.c. circuit, unless one of the following methods of separation is used:

- a) for a multicore cable or cord, the cores of the d.c. circuit are separated from the cores of the a.c. circuit by an earthed metal screen of equivalent current carrying capacity to that of the largest core in either circuit;
- b) the cables are insulated for their system voltage and installed in a separate compartment of a cable ducting or trunking system;
- c) the cables are installed on a tray or ladder where physical separation is provided by a partition;
- d) a separate conduit, sheathing or trunking system is used;
- e) the d.c. and a.c. conductors are fixed directly to a surface and separated by at least 100 mm.

**7.8** Each electrical conductor that is part of the electrical system shall have a means to identify its function in the system, except for conductors integral with engines as supplied by their manufacturers.

**7.8.1** All equipotential bonding conductors shall be identified by green or green with yellow stripe insulation, or may be uninsulated. Conductors with green or green with yellow stripe insulation shall not be used for current-carrying conductors.

**NOTE** The protective conductor of the a.c. electrical system, ISO 13297, also uses green or green with yellow stripe insulation and may be connected to the craft engine d.c. negative terminal.

**7.8.2** Means of identification other than colour for d.c. positive conductors is permitted if properly identified on the craft wiring diagram of the electrical system(s).

**7.8.3** All d.c. negative conductors shall be identified by black or yellow insulation. If the craft is equipped with an a.c. electrical system, ISO 13297, which may use black insulation for live conductors, yellow insulation shall be used for d.c. negative conductors of the d.c. system. Black or yellow insulation shall not be used for d.c. positive conductors.

**NOTE 1** In conformance with IEC 60446, conductor insulation colours of the a.c. system are:

- live conductors: black or brown
- neutral conductors: white or light blue
- protective conductors: green or green with yellow stripe

NOTE 2 A colour stripe may be added to conductor insulation for identification in the system.

NOTE 3 Craft with a.c and d.c systems should avoid the use of brown, white or light blue insulation colour in the d.c. system, unless clearly separated from the a.c conductors and identified (7.7).

**7.8.4** Conductor insulation temperature rating in engine spaces shall be 70° C minimum, and rated oil resistant, or shall be protected by insulating conduit or sleeving, and shall be derated in allowable current-carrying capacity in accordance with A.1.

**7.8.5** For additional conductor specifications see ISO 6722.

**7.8.6** Current carrying conductors of the d.c. system shall be routed above anticipated levels of bilgewater and in other areas where water may accumulate, or at least 25 mm above the level at which the automatic bilge pump switch activates.

If conductors must be routed in the bilge area, the wiring and connections shall be in IEC 60529 IP67 enclosure, as a minimum, and there shall be no connection below the foreseeable water level.

**7.8.7** Conductors shall be routed away from exhaust pipes and other heat sources which can damage the insulation.

The minimum clearance is 50 mm from water cooled exhaust components and 250 mm from dry exhaust components, unless an equivalent thermal barrier is provided.

## **8 Overcurrent protection**

**8.1** A manually reset trip-free circuit breaker or a fuse shall be installed within 200 mm of the source of power for each circuit or conductor of the system or, if impractical, each conductor shall be contained within a protective covering, such as sheathing, conduit or cable trunking, for its entire length from the source of power to the circuit breaker or fuse.

Exception:

- a) The main power feed circuit from the battery to an engine-cranking motor, if sheathed or supported to protect against abrasion and contact with conductive surfaces. See 7.2.
- b) The main power feed from the battery to the panel board (switchboard), distribution panel or fuse block, if sheathed or supported to protect against abrasion and contact with conductive surfaces. See 7.2.

NOTE If the fuse or circuit-breaker at the source of the supply conductor is sized to protect the smallest conductor in the circuit, only the fuse or circuit-breaker at the source is required.

**8.2** The voltage rating of each fuse or circuit-breaker shall not be less than the nominal circuit voltage; the current rating shall not exceed the value for the smallest size conductor in the circuit.

**8.3** Output circuits of self-limiting generators and battery chargers do not require fuses or circuit-breakers.

## **9 Panel boards (switchboards)**

**9.1** Panel boards (switchboards) shall be installed such that the control elements, indicating instruments, circuit breakers and fuses are readily accessible. The terminal side shall be accessible.

**9.2** Connections and components on panel boards shall be in locations protected from the expected conditions in conformity with IEC 60529:

— min IP 67 if exposed to short term immersion;

- min IP55 if exposed to splashing water;
- min IP 20 if located in protected locations inside the craft.

**9.3** Panel boards (switchboards) shall be permanently marked with the nominal system voltage.

EXAMPLE 12 V d.c. (or 6 V, 24 V, 32 V d.c., as appropriate for the craft)

**9.4** Craft equipped with both d.c. and a.c. electrical systems shall have their distribution from either separate panel boards or a common one with a partition or other positive means provided to separate clearly the a.c. and d.c. sections from each other. Wiring diagrams to identify circuits, components and conductors shall be included.

## 10 Wiring connections and terminals

**10.1** Conductor connections shall be in locations protected from the weather or in IEC 60529 IP 55 enclosures as a minimum. Connections above deck exposed to intermittent immersion shall be in IEC 60529 IP 67 enclosures as a minimum.

**10.2** Metals used for terminal studs, nuts and washers shall be corrosion-resistant and galvanically compatible with the conductor and terminal. Aluminum and unplated steel shall not be used for studs, nuts or washers in electrical circuits.

**10.3** All conductors shall have suitable terminals installed, i.e. no bare wires to stud or screw connections.

**10.4** Screw-clamp or screwless terminal blocks shall conform to IEC 60947-7-1. Other terminals shall be of the ring or self locking captive spade type, not dependent on screw or nut tightness alone for retention on the stud or screw.

**Exception:** friction type connectors may be used in circuits not exceeding 20 A if the connection does not separate when subjected to a force of 20 N.

**10.5** Twist-on connectors (wire nuts) shall not be used.

**10.6** Exposed shanks of terminals shall be protected against accidental shorting by the use of insulation barriers or sleeves, except for those in the grounding system.

**10.7** Solderless crimp-on terminals and connectors shall be attached with the type of crimping tool designed for the termination used and for a connection meeting the following requirements:

Conductor-to connector and conductor to terminal connection shall be capable of withstanding a tensile force equal to at least the value shown in the table for the smaller conductor in the connection, without separating:

Table 1

Conductor size mm <sup>2</sup>	Tensile force N	Conductor size mm <sup>2</sup>	Tensile force N	Conductor size mm <sup>2</sup>	Tensile force N
0,75	40	6	200	50	400
1	60	10	220	70	440
1,5	130	16	260	95	550
2,5	150	25	310	120	660
4	170	35	350	150	770

**10.8** No more than four conductor terminals shall be secured to one terminal stud.

## **11 Socket outlets**

**11.1** Socket outlets and matching plugs used on d.c. systems shall not be interchangeable with those used on a.c. systems on the craft.

**11.2** Socket outlets installed in locations subject to rain, spray or splash shall be protected to IEC 60529 IP 55 as a minimum when not in use, e.g. protected by a cover with an effective weatherproof seal.

**11.3** Socket outlets installed in areas subject to flooding or momentary submersion shall be protected to IEC 60529 IP 67 as a minimum, including when in use with connecting plugs.

## **12 Ignition protection**

**12.1** Electrical components installed in compartments which may contain explosive vapour and gases shall be ignition-protected in accordance with ISO 8846.

Compartments which may contain explosive gases are those containing or which have open connections with compartments containing such items as

- a) spark-ignition engines or their fuel tanks;
- b) joints or fittings in fuel lines connecting spark-ignition engines with their fuel tanks.

Open compartments having 0,34 m<sup>2</sup> of open area per cubic metre of compartment volume exposed to the open atmosphere outside the craft constitute an exception to this requirement.

**12.2** Electrical components installed in certain compartments in craft with LPG systems, such as lockers and housings containing LPG cylinders and pressure regulators, shall be ignition-protected (ISO 8846) as required in ISO 10239.

## Annex A (normative)

### Conductor requirements

**A.1** Table A.1 gives allowable continuous current ratings in amperes determined for 30 °C ambient temperature.

For conductors in engine rooms (60 °C ambient), the maximum current rating in Table A.1 shall be derated by the factors below:

Temperature rating of conductor insulation:	Multiply maximum current from Table A.1 by:
°C	
70	0,75
85 to 90	0,82
105	0,86
125	0,89
200	1

**A.2** As a guideline: the voltage drop  $E$  at load, in volts, may be calculated by the following formula:

$$E = \frac{0,0164 \times I \times L}{S}$$

where

$S$  is the conductor cross-sectional area, in square millimetres;

$I$  is the load current, in amperes;

$L$  is the length, in metres, of conductor from the positive power source to the electrical device and back to the negative source connection.

Table A.1 — Conductor cross sectional area, allowable continuous current and stranding

Cross-sectional area mm <sup>2</sup>	Maximum current, in amperes, for single conductors at insulation temperature ratings						Minimum number of strands	
	60 °C	70 °C	85 °C to 90 °C	105 °C	125 °C	200 °C	Type A	Type B
0,75	6	10	12	16	20	25	16	—
1	8	14	18	20	25	35	16	—
1,5	12	18	21	25	30	40	19	26
2,5	17	25	30	35	40	45	19	41
4	22	35	40	45	50	55	19	65
6	29	45	50	60	70	75	19	105
10	40	65	70	90	100	120	19	168
16	54	90	100	130	150	170	37	266
25	71	120	140	170	185	200	49	420
35	87	160	185	210	225	240	127	665
50	105	210	230	270	300	325	127	1 064
70	135	265	285	330	360	375	127	1 323
95	165	310	330	390	410	430	259	1 666
120	190	360	400	450	480	520	418	2 107
150	220	380	430	475	520	560	418	2 107

Conductors with at least Type A stranding shall be used for general craft wiring. Conductors with Type B stranding shall be used for any wiring where frequent flexing is involved in use.

NOTE Conductor current ratings may be interpolated for cross sectional areas between those shown above.

## **Annex B** (normative)

### **Information and instructions and to be included with owner's manual (ISO 10240)**

#### **B.1 The following information shall be included with the owner's manual:**

- c) diagram(s) identifying the electrical circuits of the craft with the locations of electrical devices in the craft and identification of conductors by colour or other means;
- d) location and description of functions of electrical controls, dials, switches, fuses and also circuit-breakers installed on the panel-board.

#### **B.2 The following advisory instructions shall be provided for the owner.**

 Never

- a) work on the electrical installation while the system is energized;
- b) modify the craft's electrical system or relevant drawings. Installation, alterations and maintenance should be performed by a competent marine electrical technician;
- c) alter or modify the rated current amperage of overcurrent protective devices;
- d) install or replace electrical appliances or devices with component;
- e) s exceeding the rated current amperage of the circuit;
- f) leave the craft unattended with the electrical system energized, except automatic bilge pump, fire protection and alarm circuits.

## **Annex C** (informative)

### **Recommended system tests**

The following system tests should be performed upon completion of the d.c. installation:

Continuity of circuits, particularly ring and protective circuits.

**CAUTION — Some electronic equipment may be damaged by high d.c. voltages.**

## Annex D (informative)

### Related standards and brief description of their contents

This International Standard is intended to provide protection against explosion and fires. It is important to realize that this Standard by itself is not intended to achieve this purpose. The manufacturer also needs to comply with additional standards related to protection against the same possible hazards. These additional Standards are listed below, with a brief description of their contents. For complete understanding of the requirements, the manufacturer needs to refer to the actual standard. Compliance with all these International Standards will ensure a high level of safety in all craft, particularly in those using petrol or LPG.

ISO 10088:-<sup>1)</sup>, *Small craft — Permanently installed fuel systems and fixed fuel tanks*

Individual fuel tanks, 100 % pressure tested  
 Non-metallic fuel tanks, fire tested  
 Fire resistant flexible fuel hoses  
 Fire test for non-metallic fuel system components  
 Corrosion-resistant fuel tank materials  
 Galvanically compatible metallic parts  
 Anti siphon protection requirements  
 Double clamping of fuel fill hoses  
 Electrically ground major metallic parts  
 100 % pressure test of entire fuel system

ISO 8846:1990, *Small craft — Electrical devices — Protection against ignition of surrounding flammable gases*

All components in petrol engines, petrol and LPG tank compartments to be ignition-protected to prevent open sparks. This applies to the entire engine, as well as all electrical contacts, commutators, brushes, collector rings, switches, relays, generators, fuses, distributors, engine-cranking motors, propulsion trim motors, etc.

The Standard further requires components to withstand any operating conditions of the device, including the maximum achievable overload up to 400 % of the rated current (circuit-breakers, switches and the like) and a stalled rotor condition for any motor with the circuit protected in an overcurrent protective device specified by the product manufacturer.

ISO 7840:2005, *Small craft — Fire resistant fuel hoses*

Only fire-resistant fuel hoses may be used in petrol engine and petrol fuel tank compartments. A flexible hose to be used between the engine and any solidly mounted metallic line to eliminate vibration failure. The hose to withstand fire, pressure, vacuum collapse, ozone and other environments, and have minimal fuel permeation.

ISO 9097:1991, *Small craft — Electric fans*

ISO 8849:2002, *Small craft — Electrically operated bilge-pumps*

All components, if installed in a petrol engine, petrol or LPG tank compartment to be ignition-protected, have all wiring insulated, be suitable for marine environment, and not create a hazard when the motor is overloaded or stalled.

---

1) To be published. (Revision of ISO 10088:2000)

ISO 10239:-<sup>2)</sup>, *Small craft — Liquefied petroleum gas (LPG) systems*

System to withstand temperature extremes  
Appliances approved and installed only in ventilated compartments, tanks and pressure regulators in lockers identified and vented with overboard drains  
Meet specifications for fuel lines and their supports  
Appliance well secured with flame failure shutoff control device for each appliance  
Warning labels on appliances  
Pressure test on installed system  
Any electrical device in lockers, designated for LPG storage, ignition-protected

ISO 9094-1:-<sup>2)</sup>, *Small craft — Fire protection — Craft up to and including 15 m length of hull*

ISO 9094-2:-<sup>2)</sup>, *Small craft — Fire protection — Craft with a hull length of over 15 m and up to 24 m*

Specifications for exits and emergency exits  
Material specifications in areas close to open flames  
Self-extinguishing materials in engine compartment  
Ventilation and flue protection for water heater  
Sealed combustion systems on unattended appliances  
Specification for fuel tanks  
Requirement for portable fire-extinguishers, for accessibility, protection, stowage and locker identification size  
Specification for number and types of fire-extinguishers  
Specification for fixed fire-extinguishing system on some craft  
Cylinder installation specification  
Remote release for fixed systems  
Distribution hoses and tubes fire-resistant  
Specifications for discharge and control  
Discharge and operating instructions

ISO 11105:1997, *Small craft — Ventilation of petrol engine and/or petrol tank compartments*

Ventilation amount based on compartment volume  
Specification for compartment tightness  
Natural and powered ventilation in engine compartments  
Natural ventilation in certain fuel compartments  
Ventilation openings on exterior of craft  
Blower warning for craft operator

IEC 92-350: 1988, *Electrical installations in ships Part 350: Low voltage shipboard power cables. General construction and test requirements*

IEC 92-352: 1988, *Electrical installations in ships Part 352: Choice and installation of cables for low-voltage power systems*

IEC 60446, *Identification of conductors by colours or numerals*

---

2) To be published.

## Bibliography

- [1] ISO 10088:-<sup>3)</sup>, *Small craft — Permanently installed fuel systems and fixed fuel tanks*
- [2] ISO 7840, *Small craft — Fire resistant fuel hoses*
- [3] ISO 9097, *Small craft — Electric fans*
- [4] ISO 8849, *Small craft — Electrically operated bilge-pumps*
- [5] ISO 9094-1:-<sup>4)</sup>, *Small craft — Fire protection — Craft up to and including 15 m length of hull*
- [6] ISO 9094-2:-<sup>5)</sup>, *Small craft — Fire protection — Craft with a hull length of over 15 m and up to 24 m*
- [7] ISO 10240, *Small craft — Owner's manual*
- [8] ISO 13297, *Small craft — Electrical systems — Alternating current installations*
- [9] ISO 11105, *Small craft — Ventilation of petrol engine and/or petrol tank compartments*
- [10] IEC 92-350, *Electrical installations in ships Part 350: Low voltage shipboard power cables. General construction and test requirements*
- [11] IEC 92-352, *Electrical installations in ships Part 352: Choice and installation of cables for low-voltage power systems*
- [12] IEC 60446, *Identification of conductors by colours or numerals*

---

3) To be published. (Revision of ISO 10088:2000)

4) Under revision. (Revision of ISO 9094-1:2003)

5) Under revision. (Revision of ISO 9094-2:2002)

**Annex ZA**  
(informative)

**Relationship between this International Standard and the Essential Requirements of EU Directive 94/25/EC**

By agreement between ISO and CEN, this CEN annex is included in the DIS and the FDIS but will not appear in the published ISO standard.

This International Standard has been prepared under a mandate given to CEN by the European Commission and the European Free Trade Association to provide one means of conforming to Essential Requirements of the New Approach Directive 94/25/EC.

Once this standard is cited in the Official Journal of the European Communities under that Directive and has been implemented as a national standard in at least one Member State, compliance with the normative clauses of this standard confers, within the limits of the scope of this standard, a presumption of conformity with the relevant Essential Requirements of that Directive and associated EFTA regulations.

**WARNING:** Other requirements and other EU Directives may be applicable to the products falling within the scope of this standard.